APPARATUS AND METHOD FOR DRAWING LINES

BACKGROUND OF THE INVENTION

The present invention generally relates to a graphics

5 processor for drawing lines as a graphic image on a display device, for example, and more particularly relates to an apparatus that can draw relatively short lines in a shorter amount of time.

Thanks to remarkable progress of computer graphics tech-

10 nologies, the capabilities of graphics processors, such as the quantities of data processable per unit time, have tremendously improved. Under the circumstances such as these, the need for drawing an image at an even higher resolution goes on increasing day after day. Typical applications the

15 computer graphics technologies have ever found include computer-aided design (CAD), computer-aided engineering (CAE) and computer games. Recently, however, those technologies have expanded their applications to presentation of maps on the display of a car navigation system using a global positioning

20 system (GPS).

A car navigation system, in particular, often needs to present map information (e.g., roads, boundaries, etc. on the map) on the screen as a combination of many short lines, not just simple straight lines (or line segments). Also, the

25 user's demand for accelerated line drawing by a graphics

1

processor has been rising in the field of navigation systems. This is because he or she almost always wants to retrieve information about an area neighboring that currently presented on the screen as fast as possible.

As for the techniques of drawing lines by computer graphics technologies, see Yoshio Sato, "An Introduction to Graphics", ASCII Publisher, pp. 46-56, for example.

Hereinafter, a known line-drawing method will be described with reference to Figures **25** and **26**.

Figure **25** illustrates a basic procedure taken by the known line-drawing method. Suppose a start point **100** with coordinates (Xs, Ys) and an end point **101** with coordinates (Xe, Ye) are given on the screen. In this case, to draw a line connecting the start and end points **100** and **101** together, a (linear) slope parameter, representing the slope of the line, needs to be calculated from these coordinates as │Ye−Ys│/│Xe−Xs│. Actually, though, the line is drawn as a group of line segments **102** with a unit length that are joined together between the start and end points **100** and **101**.

Figure **26** illustrates a typical flow of the known line-drawing process. As shown in Figure **26**, first, in Step **S100**, the directional attribute of a line is determined. Specifically, the shifting direction of the line is known from the signs of the differences between the X coordinates and between the Y coordinates of the start and end points **100** and

2

101, i.e., (Xe $-$ Xs) and (Ye $-$ Ys). Next, in Step **S101**, the

slope parameter of the line is obtained by dividing the abso-

lute value of the difference between the Y coordinates by

that of the difference between the X coordinates, i.e., | Ye

5   $-$ Ys | $/$ | Xe $-$ Xs | .   Then, in Step **S102**, it is determined

whether or not the far end of the line being drawn has

reached the end point **101**.   If the answer is NO, then the

slope parameters obtained are sequentially added together

from the start point **100** in the next Step **S103**.

10   As described above, in presenting detailed information

about roads as a map on a car navigation system, for example,

it is necessary to draw many short lines within a predeter-

mined amount of time. However, the conventional line-drawing

method needs to perform division operations for generating

15   slope parameters as shown in Figure **26**.   As is well known in

the art, the division operations require high computational

costs in the field of digital computations.   That is to say,

the hardware cost and the time for performing those operations

are several times greater than addition operations.   Thus, it

20   is difficult for a car navigation system, which usually pre-

sents roads and so on using short lines, to draw those lines

at sufficiently high speeds.

SUMMARY OF THE INVENTION

25   It is therefore an object of the present invention to

draw lines (or short lines, in particular) at high speeds us-
ing a simple configuration.

To achieve this object, the inventive line-drawing appa-
ratus presents a midpoint between the start and end points of
a line by generating the coordinates of the point. Then, the
apparatus sequentially presents other midpoints by generating
their coordinates such that each midpoint is located between
the midpoint previously generated and one of the other points
adjacent to the midpoint.

Specifically, a first inventive line-drawing apparatus
is adapted to draw a line connecting a start point to an end
point. The start and end points are represented by mutually
different sets of coordinates. The apparatus includes mid-
point coordinate generating means for generating coordinates
for first, second and third midpoints. The first midpoint is
located in the middle of a line segment connecting the start
and end points together. The second midpoint is located in
the middle of a line segment connecting the start point and
the first midpoint together. And the third midpoint is locat-
ed in the middle of a line segment connecting the end point
and the first midpoint together. The apparatus further in-
cludes display means for presenting the start point, the
first, second and third midpoints and the end point thereon.

In the first line-drawing apparatus, first, the midpoint
coordinate generating means generates coordinates for a first

4

midpoint located in the middle of a line segment connecting start and end points together. And then the generating means sequentially generates coordinates for other midpoints, each located in the middle of a line segment connecting two adjacent points together. Thus, in calculating a linear parameter representing the slope of the line, there is no need to perform a division operation using the difference between the X coordinates of the start and end points as a denominator. That is to say, since virtually no dividers are needed anymore, the throughput improves particularly when many short lines should be drawn. In addition, since the divide-by-two operation for obtaining each midpoint may be performed just by shifting right by one bit as for a binary number, the configuration of the apparatus can be simplified and the cost thereof can be cut down.

In one embodiment of the present invention, the midpoint coordinate generating means further generates coordinates for other midpoints, each being located in the middle of a line segment ending at two adjacent ones of the points. In such an embodiment, even if the line to be drawn is relatively long, the line still can be drawn with higher precision.

In another embodiment of the present invention, the line connecting the start and end points together is preferably divided into a number 2^n of line segments, where n is an integer equal to or greater than zero. And each said line seg-

5

ment is preferably further divided by two with the line segment regarded as ending at a new pair of start and end points. In such an embodiment, even if the line connecting the start and end points together is relatively long, that long line can be drawn by dividing the long line into multiple short lines in advance and there is no need to use the linear parameters unlike the conventional method. In addition, since this apparatus can be used recursively, the apparatus can have its configuration simplified.

In this particular embodiment, at least one midpoint is obtained by dividing the line connecting the start and end points together into a number 2^n of line segments, where n is an integer greater than zero. Each said midpoint obtained is located in the middle of a line segment connecting two of the other points, where one of the two points is located closer to the start point while the other is located closer to the end point.

A second inventive line-drawing apparatus is also adapted to draw a line connecting a start point to an end point. The start and end points are both presented on display means and represented by mutually different sets of coordinates. The apparatus includes: first and second data storage means, each accepting a plurality of input coordinate data and sequentially outputting one item of these data after another on a first in, first out basis; adding means for receiving and

6

adding together the respective coordinate data output from the first and second data storage means and outputting added data; and divide-by-two means for dividing the added data by two and outputting divided data. The coordinate data output from the

5 first and second data storage means are input to the first data storage means. The divided data is input from the divide-by-two means to the second storage means. And the line connecting the start and end points together is drawn on the display means in accordance with the divided data output from the

10 divide-by-two means.

In the second line-drawing apparatus, coordinate data, representing the start and end points, are output and stored on the first and second data storage means concurrently. Next, the output data of the first and second data storage

15 means, i.e., the coordinate data representing the start and end points, are output to the adding means. At the same time, the coordinate data representing the start and end points are stored on the first data storage means, while the divided coordinate data, representing the first midpoint, is stored on

20 the second data storage means. Since these data storage means are FIFOs, the first and second data storage means will next output the coordinate data representing the start or end point and the coordinate data representing the first midpoint, respectively. Thus, if these coordinate data output are added

25 together and the sum is divided by two, then the coordinates

7

for the second or third midpoint are generated. In this manner, the second inventive line-drawing apparatus performs the same operation as the first inventive line-drawing apparatus.

In one embodiment of the present invention, the divide-by-two means is preferably a shifter that is so interconnected as to shift the added data to the right by one bit. In such an embodiment, the divide-by-two means is implementable as a shifter (e.g., a barrel shifter) that can operate at a high speed using a simple configuration. Thus, the inventive apparatus can consist of relatively simple hardware resources including the adding means as primary components.

In another embodiment of the present invention, the second apparatus may further include iteration control means for regulating the number of times the output data is fed back to the first and second storage means. The iteration control means may include: a longer side calculator/selector for calculating respective absolute values of a difference between X coordinates and a difference between Y coordinates of the start and end points and for outputting one of these two differences that has the greater absolute value; and a number-of-times comparator for determining, by the absolute value, the number of times the output should be fed back. In such an embodiment, the longer side calculator/selector selects either the difference between the X coordinates or the difference between the Y coordinates that has the greater absolute value

for the start and end points. Accordingly, the number of mid-points .formed between the start and end points is controllable depending on the absolute values of the differences between the X coordinates and between the Y coordinates, thus increasing the line-drawing precision. In addition, since the number-of-times comparator determines the required number of times of feedback by the difference with the greater absolute value, the line-drawing process can be finished within a predetermined amount of time.

In still another embodiment, the second apparatus may further include: first and second color data storage means, each accepting a plurality of input color data and sequentially outputting one of the data after another on a first in, first out basis; color data adding means for receiving and adding together the respective color data output from the first and second color data storage means and outputting added color data; and color data divide-by-two means for dividing the added color data by two and outputting divided color data. The color data, which are output from the first and second color data storage means and correspond to the start and end points, respectively, are input to the first color data storage means. The divided color data, output from the color data divide-by-two means, is input to the second color data storage means. And the color of the line connecting the start and end points together may be determined in accordance with the divided

9

color data. Generally speaking, color information is also processed digitally by a computer. Thus, in this embodiment, the added color data is also divided by two, while the line connecting the start and end points together is being drawn. As a result, a color-interpolated, graded line can be drawn within a period of time required by the conventional division operation.

In an alternate embodiment, the second line-drawing apparatus may further include: first and second brightness data storage means, each accepting a plurality of input brightness data and sequentially outputting one of the data after another on a first in, first out basis; brightness data adding means for receiving and adding together the respective brightness data output from the first and second brightness data storage means and outputting added brightness data; and brightness data divide-by-two means for dividing the added brightness data by two and outputting divided brightness data. The brightness data, which are output from the first and second brightness data storage means and correspond to the start and end points, respectively, are input to the first brightness data storage means. The divided brightness data, output from the brightness data divide-by-two means, is input to the second brightness data storage means. And the brightness of the line connecting the start and end points together may be determined in accordance with the divided brightness data. Generally speaking,

brightness information is also processed digitally by a computer. Thus, in this embodiment, the added brightness data is also divided by two, while the line connecting the start and end points together is being drawn. As a result, a bright-

5   ness-interpolated, graded line can be drawn within a period of time required by the conventional division operation.

In yet another embodiment, the second line-drawing apparatus may further include: linear parameter calculating means for calculating and outputting a linear parameter represent-

10   ing a slope of the line connecting the start and end points together; first selecting means for receiving the linear parameter and the output data of the first data storage means and selectively outputting either the parameter or the output data of the first data storage means to the adding means; and

15   second selecting means for receiving the divided data and the output data of the second data storage means and selectively outputting either the divided data or the output data of the second data storage means to the adding means. In general, when a relatively long line should be drawn between start and

20   end points, that line could be drawn faster by the conventional method, in which the line is sequentially drawn to the end point while calculating linear parameters, than by the inventive method, in which the line segments are drawn while obtaining multiple midpoints. In this embodiment, however, the

25   apparatus includes the linear parameter calculating means for

calculating and outputting a linear parameter representing the slope of the line connecting the start and end points together. Thus, even in the situation described above, if the FIFO-type data storage means are disabled by the first and

5 second selecting means to enable the output of the linear parameter calculating means, the adding means can be shared. Accordingly, in drawing short lines, a high throughput is realizable without using the conventional dividers. On the other hand, in drawing long lines, which could not be drawn at a

10 high throughput by the short line drawing method, the configuration of the apparatus can be simplified by partially sharing the hardware.

A third inventive line-drawing apparatus is also adapted to draw a line connecting a start point to an end point. The

15 start and end points are both presented on display means and both represented by mutually different sets of coordinates. The apparatus includes: data storage means with data storage areas on which multiple coordinate data are storable, the coordinate data including first and second coordinate data of

20 the line connecting the start and end points together; adding means for adding together the first and second coordinate data and outputting added data; and divide-by-two means for dividing the added data by two and outputting divided data. The divided data is stored as third coordinate data on a predeter-

25 mined one of the data storage areas.

In the third apparatus, data storage means includes data storage areas, on which multiple coordinate data, including first and second coordinate data of a line connecting start and end points together, are storable. Accordingly, the number of midpoints to be generated is automatically determined by the number of the data storage areas (i.e., capacity). As a result, the procedure of computations is simplified and controllable more easily.

In one embodiment of the present invention, the adding and divide-by-two means repeatedly perform the addition and the divide-by-two operation for multiple line segments a number of times determined by the number of the data storage areas. Each said line segment ends at two adjacent ones of midpoints that correspond to the respective coordinate data. And results of the addition and the divide-by-two operation are stored on respectively predetermined ones of the data storage areas. In such an embodiment, even if a line segment to be drawn is relatively long, the line segment can be drawn with higher precision.

An inventive line-drawing method is adapted to draw a line connecting a start point to an end point using a line-drawing apparatus. The apparatus includes: display means; first and second data storage means of a first in, first out type; adding means for receiving outputs of the first and second data storage means; and divide-by-two means for dividing

an output of the adding means by two. The start and end points are both presented on the display means and represented by mutually different sets of coordinates. The method includes the steps of: a) outputting start and end point coordinate data, which represent the start and end points, respectively, to the display means; b) storing the start and end point coordinate data on the first and second data storage means, respectively; c) outputting the start point coordinate data from the first data storage means to the adding means and storing the start point coordinate data back to the first storage means concurrently; d) outputting the end point coordinate data from the second data storage means to the adding means and storing the end point coordinate data on the first storage means concurrently; e) outputting a sum of the start and end point coordinate data from the adding means to the divide-by-two means; and f) providing output data of the divide-by-two means to the display means and storing the output data of the divide-by-two means on the second data storage means concurrently such that the output data of the divide-by-two means corresponds to the start and end point coordinate data stored in the steps c) and d).

According to the inventive line-drawing method, short lines can be drawn easily using the second inventive line-drawing apparatus.

BRIEF DESCRIPTION OF THE DRAWINGS

Figure **1** is a schematic block diagram illustrating a line-drawing apparatus according to a first embodiment of the present invention.

Figure **2** is a block diagram illustrating the details of an X coordinate generator for the line-drawing apparatus of the first embodiment.

Figure **3** is a block diagram illustrating the details of a shifter for the line-drawing apparatus of the first embodiment.

Figure **4** is a block diagram illustrating the details of an X coordinate controller for the line-drawing apparatus of the first embodiment.

Figure **5** is a block diagram illustrating the details of an iterative number regulator for the line-drawing apparatus of the first embodiment.

Figure **6** is a block diagram illustrating the details of a number-of-times comparator for the line-drawing apparatus of the first embodiment.

Figure **7** is a schematic representation illustrating relationships between the number of stages in an FIFO memory and the value of a longer side to be drawn.

Figures **8(a)** through **8(d)** are schematic representations illustrating how the line-drawing apparatus of the first embodiment generates coordinate data for a line connecting five

pixels together:

Figure **8(a)** illustrates coordinate data for start and end points;

Figure **8(b)** illustrates coordinate data for a first midpoint located between the start and end points;

Figure **8(c)** illustrates coordinate data for second and third midpoints; and

Figure **8(d)** illustrates the coordinate data defined for the five pixels.

Figure **9** is a schematic representation illustrating how the coordinate data are stored on the FIFO memory of the line-drawing apparatus of the first embodiment.

Figure **10(a)** is a schematic representation illustrating how data is input and output to/from a four-stage FIFO memory for the line-drawing apparatus of the first embodiment; and

Figure **10(b)** is a block diagram illustrating how data is input and output to/from first and second four-stage FIFO memories for the line-drawing apparatus of the first embodiment.

Figure **11** is a schematic representation illustrating how the line-drawing apparatus of the first embodiment may perform a line-drawing operation for three pixels.

Figures **12(a)** and **12(b)** are schematic representations illustrating how the line-drawing apparatus of the first embodiment may perform a line-drawing operation for three pix-

16

els with rounding and truncation adopted, respectively.

Figures **13(a)** and **13(b)** are schematic representations illustrating how the line-drawing apparatus of the first embodiment may perform a line-drawing operation for four pixels with rounding and truncation adopted, respectively.

Figures **14(a)** through **14(c)** illustrate a method using a fixed memory for a line-drawing apparatus according to a modified example of the first embodiment:

Figure **14(a)** is a schematic representation illustrating a fixed memory that stores data for nine pixels thereon;

Figure **14(b)** illustrates the order in which coordinates of respective midpoints should be calculated and the locations where those midpoint coordinate data should be stored; and

Figure **14(c)** is a schematic representation illustrating a fixed memory that stores data for five pixels thereon.

Figure **15** is a schematic block diagram illustrating a line-drawing apparatus according to a second embodiment of the present invention.

Figure **16** is a schematic representation illustrating an exemplary graded line drawn with their colors interpolated by the line-drawing apparatus of the second embodiment.

Figure **17** is a schematic block diagram illustrating a modified example of a color information generator in the line-drawing apparatus of the second embodiment.

Figure **18** is a schematic block diagram illustrating a line-drawing apparatus according to a third embodiment of the present invention.

Figure **19** is a block diagram illustrating a parameter calculator and the details of an X coordinate generator for a line-drawing apparatus according to a fourth embodiment of the present invention.

Figure **20** is a block diagram illustrating the details of an iterative number regulator for the line-drawing apparatus of the fourth embodiment.

Figure **21** is a flowchart illustrating how the iterative number regulator may determine the number of times the line-drawing apparatus should perform the operation according to the fourth embodiment.

Figure **22** is a block diagram illustrating the details of an X coordinate generator for a line-drawing apparatus according to a fifth embodiment of the present invention.

Figures **23(a)** through **23(c)** are schematic representations illustrating how to divide a long line into multiple short lines according to the fifth embodiment:

Figure **23(a)** illustrates a long line to be drawn;

Figure **23(b)** illustrates two short lines obtained by dividing the long line shown in Figure **23(a)** into two; and

Figure **23(c)** illustrates four short lines obtained by further dividing each of the short lines shown in Figure

18

23(b) into two.

Figure **24** is a block diagram illustrating the details of a number-of-times comparator for the line-drawing apparatus of the fifth embodiment.

5   Figure **25** is a schematic representation illustrating a known line-drawing method.

Figure **26** is a flowchart illustrating respective process steps of the known line-drawing method.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

EMBODIMENT 1

Hereinafter, a first embodiment of the present invention will be described with reference to the accompanying drawings.

Figure **1** illustrates a configuration for a line-drawing apparatus of the first embodiment. As shown in Figure 1, the line-drawing apparatus includes parameter register **1**, X and Y coordinate generators **2** and **3**, address converter **4**, memory interface **5**, frame memory **6** and image display **7**. Coordinate

20   data, representing an image to be drawn, is temporarily stored on the parameter register **1**. X and Y coordinates, included in the coordinate data, are generated by the X and Y coordinate generators **2** and **3**, respectively. The address converter **4** converts the two-dimensional coordinate data, generated by the X

25   and Y coordinate generators **2** and **3**, into one-dimensional co-

ordinate data, which is passed to, and stored on, the frame

memory 6 for storing image frames via the memory interface 5.

Then, the coordinate data is eventually presented on the image

display 7 such as a liquid crystal display panel or a CRT. On

5 receiving an end-of-drawing signal, the memory interface 5

stops outputting the coordinate data to the frame memory 6.

Figure 2 illustrates the details of the X coordinate

generator 2 shown in Figure 1. Although not shown, the Y co-

ordinate generator 3 also has a similar configuration to that

10 of the X coordinate generator 2. As shown in Figure 2, the X

coordinate generator 2 includes first and second FIFO memories

11 and 12, X coordinate calculator 13, X coordinate controller

14 and selector 15. The first and second FIFO memories 11 and

12 may receive the X coordinates of the start and end point

15 coordinate data, respectively, from the parameter register 1

and store them thereon. The X coordinate calculator 13 re-

ceives and adds together the output data of the first and sec-

ond FIFO memories 11 and 12, divides the sum by two and then

outputs the quotient. The X coordinate controller 14 is an

20 exemplary iteration control means for controlling the itera-

tive operation of the first and second FIFO memories 11 and

12, for example, as defined in the appended claims. The se-

lector 15 receives the two output data of the parameter regis-

ter 1 and the output data of the X coordinate calculator 13

25 and selectively outputs one of these three data in response to

a select signal supplied from the X coordinate controller **14**.

The first FIFO memory **11** includes first and second memory cells **11a** and **11b**. One of the two output data of the parameter register **1** and the output data of the second FIFO memory **12** are input to the first memory cell **11a**. The output data of the first memory cell **11a** and that of the first FIFO memory **11** are input to the second memory cell **11b**.

The second FIFO memory **12** also includes first and second memory cells **12a** and **12b**. The other output data of the parameter register **1** and the output data of the X coordinate calculator **13** are input to the first memory cell **12a**. The output data of the first memory cell **12a** and that of the X coordinate calculator **13** are input to the second memory cell **12b**. It should be noted that the same operation is executable even if the first and second FIFO memories **11** and **12** have their positions interchanged horizontally.

The X coordinate calculator **13** includes an adder **21** and a shifter **22**. The adder **21** receives and adds together the output data of the first and second FIFO memories **11** and **12**. The shifter **22** is an exemplary divide-by-two means for dividing the sum by two as defined in the appended claims.

In the illustrated embodiment, the shifter **22** preferably has the configuration shown in Figure **3**. Specifically, the shifter **22** preferably includes a one-bit line shifter **22a** and a data latch **22b**. The one-bit line shifter **22a** is a barrel

shifter, which has been so interconnected as to be shifted right by one bit such that the input data can be shifted to the right by one bit. The data latch **22b** latches the output values of the one-bit line shifter **22a** bit by bit and output

5 them as serial data. In such an embodiment, the circuit configuration of the shifter **22** can be simplified and the input can be divided by two at a higher speed.

Figure **4** illustrates the details of the X coordinate controller **14**. In Figure **4**, the X coordinate controller **14** in-

10 cludes iterative number regulator **25** and first and second FIFO controllers **26A** and **26B**. The iterative number regulator **25** determines how many times the output data should be fed back to the first and second FIFO memories **11** and **12**, i.e., the number of times the operation of obtaining a midpoint should

15 be performed. Following the instruction issued from the iterative number regulator **25**, the first and second FIFO controllers **26A** and **26B** control the input and output of data to/from the first and second FIFO memories **11** and **12**, respectively.

Figure **5** illustrates the details of the iterative number

20 regulator **25**. As shown in Figure **5**, the iterative number regulator **25** includes longer side calculator/selector **25a**, number-of-times comparator **25b** and operation controller **25c**. Receiving the start and end point coordinates (Xs, Ys) and (Xe, Ye) of a line to be drawn from the parameter register **1**,

25 the longer side calculator/selector **25a** obtains the absolute

22

values of the difference between the X coordinates and the difference between the Y coordinates of these two points, i.e., $|Xe - Xs|$ and $|Ye - Ys|$, and outputs one of these two differences with the greater absolute value. That is to say, the longer side calculator/selector **25a** selectively outputs the data corresponding to the longer side. The number-of-times comparator **25b** determines, by the value of the longer side, the number of times the operation should be performed and outputs the number. In response, the operation controller **25c** gets a predetermined operation executed by the X coordinate calculator **13** the given number of times.

Figure **6** illustrates an exemplary configuration for the number-of-times comparator **25b** and operation controller **25c**. As shown in Figure **6**, the number-of-times comparator **25b** includes a ROM table **251**. The operation controller **25c** includes counter **252**, comparator **253** and iterative number control signal output circuit **254**. The value of the longer side and the predetermined number of times the operation should be performed (which number has been determined by the longer-side value) are stored on the ROM table **251**. The counter **252** counts the number of times the operation has actually been performed. The comparator **253** compares the predetermined number of times, which has been read out from the ROM table **251**, to the count output from the counter **252**. If the count is still less than the predetermined number, then the comparator

253 outputs an execute signal. Alternatively, if the count is already equal to or greater than the predetermined number, then the comparator 253 outputs an end-of-operation signal.

In response to the execute signal, the iterative number control signal output circuit 254 outputs a counter control signal to the counter 252 to instruct the counter 252 to keep counting, and also outputs the execute signal to the first and second FIFO controllers 26A and 26B. On receiving the end-of-operation signal, the iterative number control signal output circuit 254 outputs an initialize signal to the counter 252 to instruct the counter 252 to reset the count and also outputs the end-of-operation signal to the first and second FIFO controllers 26A and 26B.

The ROM table 251 does not have to be a table on a memory area, but may be a logic circuit that receives the longer-side value and outputs the number of times determined by the longer-side value.

In the illustrated embodiment, the number of memory cells in each of the FIFO memories 11 and 12 (which will be herein referred to as the "number of FIFO stages") is four. Hereinafter, a relationship between the number of FIFO stages and the number of midpoints including the start and end points will be described. Also, each midpoint of a line, which is represented by X and Y coordinates, will be herein called a "line point". That is to say, the "longer-side value" is the

number of line points that together make the line.

The following Table 1 illustrates the contents of an iterative number determination table showing the relationships among the number of FIFO stages, the longer-side value and the number of times the operation should be performed repeatedly:

[Table 1]

Index (Id)	Number of FIFO Stages (2^{id+1})	Longer-side Value ($n = 2^{(id+1)} + 1$)	Number of Times of Operation ($n - 2$)
0	2	3	1
1	4	5	3
2	8	9	7
3	16	17	15
4	32	33	31
5	64	65	63

Figure **7** schematically illustrates how the value of the longer side to be drawn increases with the increase in number of FIFO stages. The following Table 2 illustrates an exemplary iterative number determination table (i.e., example of the ROM table **251**) used to determine, by the longer-side value output from the longer side calculator/selector **25a**, how many times the operation should be performed repeatedly for an FIFO memory with four stages.

[Table 2]

Longer-Side Value	Number of times of Operation
1(0001)	1
2(0010)	1
3(0011)	1
4(0100)	3
5(0101)	3
6(0110)	7
7(0111)	7
8(1000)	7
9(1001)	7

As can be seen from Table 1, the longer-side value or the number of times of operation, which is a function of the number (2^{id+1}) of FIFO stages, can be represented as a general formula.

Hereinafter, it will be described with reference to the accompanying drawings how the line-drawing apparatus with such a configuration operates. Although the operation of the X coordinate generator **2** will be detailed in the following description, the same statement is applicable to the Y coordinate generator **3**. Figures **8(a)** through **8(d)** schematically illustrate how to generate the coordinates for start point, end point and other midpoints. In Figure **8(a)**, the start and end point coordinate data are identified by **30** and **31**, respectively. In Figure **8(b)**, first midpoint coordinate data **32** represents a midpoint of a line segment connecting the start and end points that are represented by the coordinate data **30** and **31**, respectively. In Figure **8(c)**, second midpoint coordinate data **33** represents a midpoint of a line segment connecting the start point and the first midpoint that are represented by the coordinate data **30** and **32**, respectively. Also, third midpoint coordinate data **34** represents a midpoint of a line segment connecting the end point and the first midpoint that are represented by the coordinate data **31** and **32**, respectively. And Figure **8(d)** illustrates the coordinate data finally defined for these five pixels. As used

herein, the "pixel" refers to a point essential for a line to be drawn.

Figure **9** schematically illustrates how the coordinate data **30** through **34** are stored on the first and second FIFO

5 memories **11** and **12**. In Figure **9**, the same components as those illustrated in Figure **2** will be identified by the same reference numerals and the description thereof will be omitted herein.

First, as shown in Figures **2** and **9**, the coordinate data

10 **30** and **31** for the start and end points to be drawn with respective coordinates (Xs, Ys) and (Xe, Ye) are input to, and stored on, the parameter register **1**.

Next, Xs data, i.e., the X coordinate of the start point, is input from the parameter register **1** to the first

15 FIFO memory **11** and stored on the memory **11**. At the same time, the X coordinate controller **14** instructs the selector **15** to output the Xs data to the address converter **4** shown in Figure **1**. On the other hand, Xe data, i.e., the X coordinate of the end point, is input to, and stored on, the second FIFO

20 memory **12**, while the X coordinate controller **14** instructs the selector **15** to output the Xe data to the address converter **4** along with the Xs data. As a result, the start and end point coordinate data **30** and **31** shown in Figure **8(a)** are generated.

Then, the start and end point coordinate data **30** and **31**

25 are respectively input from the first and second FIFO memo-

27

ries **11** and **12** to the X coordinate calculator **13**.   At the same

time, the start point coordinate data **30**, which is output from

the first FIFO memory **11**, is input again as data **30A** to the

first FIFO memory **11** as shown in Figure **9**.   Thereafter, the

5   end point coordinate data **31**, which is output from the second

FIFO memory **12**, is input again as data **31A** to the first FIFO

memory **11**.   In this case, although these data are identified

by different reference numerals **30A** and **31A** for illustrative

purposes, these data have the same data values as the start

10   and end point coordinate data **30** and **31**, respectively.   The

same statement is applicable to data **32A** and **32B** to be de-

scribed below.

The X coordinate calculator **13** adds together the start

and end point coordinate data **30** and **31** and divides the sum

15   by two, thereby outputting first midpoint coordinate data **32**.

At the same time, the first midpoint coordinate data **32** is

input again to the two memory cells in the second FIFO memory

12 and stored thereon as data **32A** and **32B**.   As a result, the

first midpoint coordinate data **32** shown in Figure **8(b)** is

20   generated.

Subsequently, as shown in Figure **9**, the start point co-

ordinate data **30A** and the first midpoint coordinate data **32A**

are respectively input from the first and second FIFO memo-

ries **11** and **12** to the X coordinate calculator **13**.   As a re-

25   sult, the second midpoint coordinate data **33** shown in Figure

28

8(c) is generated.

Next, the end point coordinate data **31A** and the first midpoint coordinate data **32B** are respectively input from the first and second FIFO memories **11** and **12** to the X coordinate calculator **13**. As a result, the third midpoint coordinate data **34** shown in Figure **8(c)** is generated. In this manner, as for five line points (or pixels), the X coordinate calculator **13** has to perform the add-and-divide-by-two operation three times.

Then, the address converter **4** converts the two-dimensional coordinates, consisting of the X and Y coordinates output from the X and Y coordinate generators **2** and **3**, respectively, into one-dimensional coordinates as shown in Figure **1**. These one-dimensional coordinates are written as a frame image on the frame memory **6** by way of the memory interface **5**. And the image is eventually presented on the image display **7**.

Hereinafter, a specific configuration for the first and second FIFO memories **11** and **12** and a method of inputting and outputting data thereto/therefrom will be described.

Figure **10(a)** schematically illustrates the first FIFO memory **11** with four FIFO stages. The second FIFO memory **12** may also have a configuration similar to that illustrated in Figure **10(a)** for the first FIFO memory **11**. The number of FIFO stages should be determined in advance by the longer-side val-

ciated stage and higher-level stages of the data storage section 111 are invalid.

In this case, a single data unit is output by shifting the data on the first stage of the data storage section 111 downward by one stage. For example, as can be seen from the FIFO memory 11 shown at the center of Figure 10(a), when the data "0" on the first stage is output from the memory 11, each of the data "8" and "4" and the end mark "1" is shifted downward by one stage. Thereafter, when two data units "2" and "1" are input to the data storage section 111, these data units are stored on the third and fourth stages of the data storage section 111, respectively, and the end mark "1" is shifted upward by two stages to be stored on the overflow section 113 as shown on the right-hand side of Figure 10(a).

If another data is input to the data storage section 111 after the end mark "1" has been stored on the overflow section 113, then the end mark "1" is written on the overflow section 113 again and no data will be stored on the data storage section 111. On the other hand, if the data "8" is output in this state, then the end mark "1" is shifted to the fourth stage and "0" is written on the overflow section 113.

Figure 10(b) illustrates the flow of data from the parameter register 1 to the X coordinate calculator 13 through the first and second FIFO memories 11 and 12 with such a configuration. In the illustrated embodiment, the data is input

31

ue of a line to be drawn by the line-drawing apparatus. For example, as shown in Table 1, if the line has a longer-side value of 5, then each FIFO memory should have four stages. And if the line has a longer-side value of 9, then each FIFO

5   memory should have eight stages.

The first FIFO memory 11 preferably has the configuration shown in Figure 10(a). Specifically, the first FIFO memory 11 includes data storage section 111 and end mark storage section 112. The data storage section 111 has memory areas with a

10 width of at least 8 bits, while the end mark storage section 112 has memory areas with a width of 1 bit. The fifth stage of the end mark storage section 112 is an overflow section 113. Data input to the data storage section 111 is stored on a vacant area adjacent to the area where valid data has al-

15 ready been stored. On the other hand, data, which is output first from the data storage section 111, is on the first one of the stages where valid data have been stored.

In the FIFO memory 11 on the left-hand side of Figure 10(a), data "0", "8" and "4" are respectively stored on the

20 first, second and third stages of the data storage section 111. And "0" is stored on each of the three associated stages of the end mark storage section 112. This means that each of the data stored on the data storage section 111 is valid. On the fourth stage of the end mark storage section 112, an end

25 mark "1" is stored, which means that data stored on the asso-

to each of the FIFO memories **11** and **12** via a selector **MPX** and output from each of the FIFO memories **11** and **12** by way of a buffer.

Hereinafter, specific examples will be described with numerical values actually assigned to the coordinate data.

Figure **11** illustrates an example in which the start and end point coordinate data (**Xs, Ys**) and (**Xe, Ye**) are (0, 0) and (2, 2), respectively. As can be easily understood, midpoint coordinate data (1, 1) is generated just by performing the operation only once for three pixels as shown in Figure **11**.

Figure **12(a)** illustrates an example in which the start and end point coordinate data (**Xs, Ys**) and (**Xe, Ye**) are (0, 0) and (2, 1), respectively. In this case, a decimal point calculation will result in a midpoint with coordinate data (1, 0.5). Thus, the resulting data is raised (or rounded) to generate midpoint coordinate data (1, 1). The rounding operation may be performed by providing below-decimal-point bit domains for the shifter **22** shown in Figure **3** and by adding one to one bit below the decimal point. Specifically, if the one bit below the decimal point is "0" after shifting, no carries will be caused. Alternatively, if the one bit is "1", carries will be caused and 0.5 will be raised to 1.

On the other hand, Figure **12(b)** illustrates an example in which the calculated data (1, 0.5) is truncated to gener-

32

ate alternative midpoint coordinate data (1, 0). This data

is output when no below-decimal-point bit domains are provid-

ed for the shifter **22**. That is to say, the shifter **22** shown

in Figure **3** generates this data.

Figure **13(a)** illustrates an example in which the start

and end point coordinate data (Xs, Ys) and (Xe, Ye) are (0,

0) and (2, 3), respectively. The midpoint coordinate data to

be generated step by step will be enumerated below. In the

following description, an arithmetic sign "#" means an arith-

metic operation of dividing a sum of two data by two. Also,

in the following example, data with a decimal fraction is

rounded (or raised).

For Start and End Point Coordinates (0, 0) and (2, 3)

Step 1: (0, 0)#(2, 3)→(1, 1.5)→(1, 2)

Step 2: (0, 0)#(1, 2)→(0.5, 1)→(1, 1)

Step 3: (2, 3)#(1, 2)→(1.5, 2.5)→(2, 3)

On the other hand, Figure **13(b)** illustrates midpoint co-

ordinate data resulting from truncation.

For Start and End Point Coordinates (0, 0) and (2, 3)

Step 1: (0, 0)#(2, 3)→(1, 1.5)→(1, 1)

Step 2: (0, 0)#(1, 1)→(0.5, 0.5)→(0, 0)

Step 3: (2, 3)#(1, 1)→(1.5, 2)→(1, 2)

As shown in Figures **13(a)** and **13(b)**, the same image will be

drawn in both of these cases.

In the foregoing embodiment, the X and Y coordinate gen-

33

erators **2** and **3** are separately provided to perform calculation for respective coordinates. However, since X and Y coordinates are mutually independent data, just one of these coordinate generators may be provided and used repeatedly.

As described above, according to this embodiment, a short line can be drawn without performing the division operation of calculating a linear parameter for the line. That is to say, since many clock cycles, which are usually required for the division operation, are not needed, short line drawing can be started while the division cycles are still being executed according to the conventional technique. Thus, the coordinates of a line can be calculated at a higher speed. Particularly when a large number of short lines should be drawn, much more computational process is executable within a predetermined amount of time. As a result, the throughput of the drawing process can be improved considerably.

Also, in the foregoing embodiment, the FIFO memories are used for storing data to be passed to the X coordinate calculator **13**. Alternatively, any other data storage means may be used instead of the FIFO memories so long as the storage means can pass the same data as the stored one.

Modified Example of Embodiment 1

Hereinafter, a method using a fixed memory instead of the FIFO memories will be described as a modified example of

the first embodiment.

Figure **14(a)** schematically illustrates a fixed memory for storing thereon the data to be passed to the X coordinate calculator **13**. The fixed memory **45**, i.e., exemplary data storage means as defined in the claims, has its number of stages determined in advance by the longer-side value of a line to be drawn by the line-drawing apparatus. For example, if the longer-side value is 9, then a data storage section with nine stages is needed as shown in Figure **14(a)**. If the longer-side value is 17, then a storage section with 17 stages is needed. That is to say, supposing the method using an FIFO memory needs a storage section with a number m of stages (where m is a positive integer), the method using a fixed memory needs a storage section with a number m+1 stages. However, the fixed memory **45** is implementable as a single block, whereas the method using the FIFO memories needs two blocks.

Figure **14(b)** illustrates the order in which the coordinate data should be stored on the fixed memory **45**. First, the storage areas for the start and end points **1** and **9** of a line to be drawn are determined. In the illustrated example, the coordinate data of the start and end points **1** and **9** are stored on the data storage areas **A1** and **A9**, respectively.

Next, the X coordinate calculator **13**, including the adder **21** and the shifter **22** shown in Figure **2**, performs the addition

and the divide-by-two operation to obtain the coordinate data of the first midpoint 5 between the start and end points 1 and 9 and store the data on the data storage area A5. Subsequently, following the order of calculation shown in Figure 14(b), the data of the second midpoint 3 between the start point 1 and the first midpoint 5 is stored on the data storage area A3 and then a similar operation will be performed sequentially. In Figure 14(b), (A5) denotes the data stored on the data storage area A5.

By repeatedly performing this operation seven times for the line with a longer-side value of 9, the coordinate data (A2) through (A8) for all of the seven midpoints can be obtained.

The coordinate data of the midpoints do not have to be calculated in the order shown in Figure 14(b), but may be calculated in any arbitrary order so long as the coordinate data already obtained is used. In the illustrated example, the data storage areas A1 through A9 of the fixed memory 45 are arranged in the ascending or descending order of the addresses for the memory (i.e., from the start point toward the end point). However, the data storage areas A1 through A9 may be arranged in any order so long as one-to-one correspondence is established between the data obtained and their storage areas. Furthermore, each pair of data storage areas does not have to be adjacent to each other.

In the method using the fixed memory according to this modified example, even if the longer-side value is 5, the operation shown in Figure 14(b) can be performed without changing the control method in any way as shown in Figure 14(c). In this case, the data stored on the data storage areas **A9** and **A8** have the same value and the same image will be drawn twice. However, there will be no problems in the line drawing process itself. In this modified example, the same amount of time is needed for each of the longer-side values of 3 through 9.

As can be seen, according to this modified example, the control can be simplified compared to the method using the FIFO memories, because the same method is applicable to the calculation of midpoints and the memory is fixed.

EMBODIMENT 2

Next, a second embodiment of the present invention will be described with reference to the accompanying drawings.

Figure 15 illustrates a configuration for a line-drawing apparatus of the second embodiment. In Figure 15, the same components as those illustrated in Figure 1 will be identified by the same reference numerals and the description thereof will be omitted herein. As shown in Figure 15, this apparatus further includes a color information generator 8, which has a similar configuration to that of the X and Y coor-

dinate generators 2 and 3, between the parameter register 1 and the memory interface 5.

The line-drawing apparatus of the second embodiment can perform color interpolation on a line connecting start and end points where color information is added to the coordinate data representing the line including the start and end points.

Hereinafter, it will be described how the line-drawing apparatus with such a configuration operates.

In Figure 15, first, start and end point coordinate data, to which respective color data values have been assigned, are stored on the parameter register 1.

Next, as in the first embodiment, the X and Y coordinates of the start and end point coordinate data are input to the X and Y coordinate generators 2 and 3. Then, the operation is performed a predetermined number of times to obtain the coordinate data representing the first, second, third midpoints and so on, which are subsequently output to the address converter 4. In parallel with this operation, the color data values of the start and end point coordinate data are input to the color information generator 8. As in the coordinate computation, the color information generator 8 adds together the numerical values representing the colors of the start and end points and divides the sum by two, thereby outputting a piece of color interpolation information. Accordingly, the color

38

information generator **8** may have the same configuration as the

X coordinate generator **2** shown in Figure **2**. That is to say,

in this case, the first and second FIFO memories **11** and **12**,

adder **21** and shifter **22** function as first and second color da-

5   ta storage means, color data adding means and color data di-

vide-by-two means, respectively.

The interpolation information, which has been generated

by the color information generator **8**, is combined with its

associated coordinate data in the frame memory **6**. Then, a

10   pixel in the specified color is drawn on the image display **7**.

Figure **16** illustrates an exemplary line that has been

drawn with various gradations, or with its colors interpo-

lated. As used herein, the "gradation" refers to gradual

change in colors of separately located, discrete objects with

15   the interpolation. As shown in Figure **16**, the midpoint with

the coordinates (1, 1) between the dark—colored start point

with the coordinates (0, 0) and the light-colored end point

with the coordinates (2, 2) has color data representing an

intermediate color between them.

20   Figure **17** illustrates a modified example of the color

information generator **8**.

The color information generator **8** shown in Figure **17** in-

cludes red, green and blue information generators **8a**, **8b** and

8c, each having the same configuration as that of the X coor-

25   dinate generator **2**. Thus, if the color information is repre-

39

sented in terms of data for the three primary colors of red, green and blue, this apparatus can perform color interpolation with even higher precision.

As described above, the apparatus according to this embodiment uses no dividers, which are usually needed in a conventional apparatus and adversely increase the computational costs, even in drawing a short line that should have some gradation. Thus, the apparatus can draw such a line at a higher speed with its hardware configuration simplified.

If the number of FIFO stages is relatively small, the single color information generator 8 may be used in common for obtaining respective data for red, green and blue.

EMBODIMENT 3

Next, a third embodiment of the present invention will be described with reference to the accompanying drawings.

Figure 18 illustrates a configuration for a line-drawing apparatus of the third embodiment. In Figure 18, the same components as those illustrated in Figure 1 will be identified by the same reference numerals and the description thereof will be omitted herein. As shown in Figure 18, this apparatus further includes brightness information generator 9 and color data scaler 10 between the parameter register 1 and the memory interface 5. The brightness information generator 9 has a similar configuration to that of the X and Y coordinate

generators **2** and **3**. The color data scaler **10** receives the output of the brightness information generator **9**, performs color data scaling with reference to the brightness data and then outputs the scaled information to the memory interface **5**.

5   The line-drawing apparatus of the third embodiment can perform brightness interpolation on a line connecting start and end points where brightness (or luminance) information is added to the coordinate data representing the line including the start and end points.

10   Hereinafter, it will be described how the line-drawing apparatus with such a configuration operates.

In Figure **18**, first, start and end point coordinate data, to which respective brightness data values have been assigned, are stored on the parameter register **1**.

15   Next, as in the first embodiment, the X and Y coordinates of the start and end point coordinate data are input to the X and Y coordinate generators **2** and **3**. Then, the operation is performed a predetermined number of times to obtain the coordinate data representing the first, second, third mid-

20   points and so on, which are subsequently output to the address converter **4**. In parallel with this operation, the brightness data values of the start and end point coordinate data are input to the brightness information generator **9**. As in the co-ordinate computation, the brightness information generator **9**

25   adds together the numerical values representing the brightness

of the start and end points and divides the sum by two, thereby outputting a piece of brightness interpolation information. Accordingly, the brightness information generator 9 may have the same configuration as the X coordinate generator 2 shown

5   in Figure 2. That is to say, in this case, the first and second FIFO memories 11 and 12, adder 21 and shifter 22 function as first and second brightness data storage means, brightness data adding means and brightness data divide-by-two means, respectively.

10   Next, the brightness data generated is input to the color data scaler 10, which performs color data scaling with reference to the brightness data. In this case, the scaling is performed by regarding brightness values 0 and 1 as representing relatively dark and relatively bright colors, respec-

15   tively. Accordingly, if a line to be drawn has start and end points with respective brightness values 0 and 1, then the brightness of its midpoint will calculate as 0.5. By integrating this value with the color data, brightness-indexed color data can be obtained.

20   Then, the brightness-indexed color interpolation information, which has been generated by the color data scaler 10, is combined with its associated coordinate data in the frame memory 6. Then, a pixel in the specified color and with the specified brightness is drawn on the image display 7.

25   As described above, the apparatus according to this em-

bodiment uses no dividers, which are usually needed in a conventional apparatus and adversely increase the computational costs, even in drawing a short line that should be provided with some gradation in accordance with brightness-indexed color information. Thus, the apparatus can draw such a line at a higher speed with its hardware configuration simplified.

In the foregoing embodiment, a single piece of color information is associated with multiple brightness data values. Alternatively, those brightness data values may be defined for each of the three primary colors as in the modified example of the second embodiment.

Optionally, the brightness information generator 9 and the color data scaler 10 of the third embodiment may also be added to the line-drawing apparatus of the second embodiment. In such an embodiment, the line-drawing apparatus can perform both brightness and color interpolations in drawing a line.

EMBODIMENT 4

Next, a fourth embodiment of the present invention will be described with reference to the accompanying drawings.

Figure 19 illustrates a detailed configuration for an X coordinate generator in a line-drawing apparatus of the fourth embodiment. In Figure 19, the same components as those illustrated in Figure 2 will be identified by the same reference numerals and the description thereof will be omitted herein.

The line-drawing apparatus according to any of the fore-going embodiments is adapted to draw a short line as a collection of points within a predetermined amount of time. In contrast, the line-drawing apparatus of the fourth embodiment takes advantage of the conventional method of calculating a linear parameter representing the slope of a line to be drawn. Specifically, the line-drawing apparatus of this embodiment selectively adopts the method of generating multiple midpoints successively or the conventional method of calculating the linear parameter depending on the longer-side value (i.e., the number of pixels).

As shown in Figure 19, the line-drawing apparatus further includes a parameter calculator 41. The parameter calculator 41 receives the start and end point coordinate data from the parameter register 1, calculates the slope of a line including the start and end points represented by the coordinate data received and then outputs the slope to the X coordinate calculator 13.

The X coordinate generator 2 further includes first, second and third selectors 42, 43 and 44 implemented as the first, second and third selecting means as defined in the appended claims. The first selector 42 receives the output values of the first FIFO memory 11 and the parameter calculator 41 and selectively outputs one of these values to the X coordinate calculator 13. The second selector 43 receives the

44

output values of the second FIFO memory **12** and the X coordinate calculator **13** and selectively outputs one of these values to the X coordinate calculator **13**. And the third selector **44** receives the respective output values of the parameter register **1**, adder **21** and shifter **22** and selectively outputs one of these values to the address converter **4**.

Figure **20** illustrates a detailed configuration for an iterative number regulator **25** in the X coordinate controller **14** according to the fourth embodiment. In Figure **20**, the same components as those illustrated in Figure **5** will be identified by the same reference numerals and the description thereof will be omitted herein. As shown in Figure **20**, the iterative number regulator **25** further includes a line-drawing method determiner **25d**. The line-drawing method determiner **25d** receives the output of the longer side calculator/selector **25a** and determines whether or not the absolute value of the difference between X or Y coordinates of the start and midpoint coordinate data exceeds a predetermined value. If the absolute value is greater than the predetermined value, then the line-drawing method determiner **25d** generates and outputs a line-drawing method determination signal to the first and second selectors **42** and **43** such that the output of the parameter calculator **41** is selected.

Hereinafter, it will be described how the line-drawing apparatus with such a configuration operates.

45

In drawing a short line, the line-drawing apparatus operates just as described in the first embodiment. On the other hand, in drawing a long line, the line-drawing apparatus adopts the conventional line-drawing method. Thus, it will be mainly described with reference to the processing flow shown in Figure 21 how the iterative number regulator 25 shown in Figure 20 determines which of the long and short line drawing methods should be taken.

Figure 21 is a flowchart illustrating how the iterative number regulator 25 determines the line-drawing method to take according to the fourth embodiment.

First, the longer side calculator/selector 25a performs a longer side calculation and selection process shown in Figure 21. Specifically, supposing the coordinate data representing the start and end points to be drawn are (Xs, Ys) and (Xe, Ye), respectively, the longer side calculator/selector 25 obtains the respective absolute values of the difference between the X coordinates (| Xe − Xs |) and the difference between the Y coordinates (| Ye − Ys |) for the start and end points and outputs one of these differences with the greater absolute value.

Next, the line-drawing method determiner 25d determines whether or not the absolute value, output from the longer side calculator/selector 25a, is greater than a predetermined longer-side value (or the predetermined number of pixels).

Suppose the absolute value is greater than a longer-side value of 9, for example. In such a case, the determiner **25d** makes the first selector **42** select the output signal of the parameter calculator **41** and makes the second selector **43** select the output signal of the X coordinate calculator **13**. And the determiner **25d** outputs a line-drawing method determination signal, which disables the output signal of the shifter **22**, to the third selector **44**. Alternatively, if the absolute value is equal to or less than the nine-pixel-equivalent value, the determiner **25d** makes the first and second selectors **42** and **43** select the output signals of the first and second FIFO memories **11** and **12**, respectively. And the determiner **25d** outputs a line-drawing method determination signal, which disables the output signal of the adder **21**, to the third selector **44**.

Subsequently, the number-of-times comparator **25b** shown in Figure **20** determines, based on the data provided from the longer side calculator/selector **25a**, how many times the operation should be performed. Supposing the iterative number determination table shown in Table 2 is used, if the number of pixels is three or less, then the operation should be performed just once as shown in Figure **21**. Using the same table, the operation will be performed three and seven times, respectively, for five pixels or less and nine pixels or less, respectively.

By providing the line-drawing method determiner **25d**, parameter calculator **41** and selectors **42**, **43** and **44**, a long line can be drawn just as intended if the number of pixels is nine or more.

The line-drawing method determiner **25d** may also be connected to receive the output of the number-of-times comparator **25b**. In such an embodiment, there is no need to perform the process of determining whether the output of the longer side calculator/selector **25a** exceeds a predetermined value such that the long line drawing method is adopted for nine pixels or more.

As described above, the line-drawing apparatus of the fourth embodiment can generate coordinates for any line using the same computational resource, i.e., the adder **21** in this case, no matter whether the line to be drawn is long or short. Thus, even when short and long lines both should be drawn, a hardware resource can be shared without providing any additional adder **8**.

Moreover, in drawing a short line, there is no need to perform the division operation using the difference of X coordinates, which is required in drawing a long line. Thus, compared to the conventional technique, coordinates for a short line can be obtained faster and the overall throughput of the line-drawing process can be improved.

In the foregoing embodiment, the "short line" is sup-

posed to correspond to nine pixels or less. However, the present invention is not limited to this specific value.

Accordingly, although the number of FIFO stages is four in the foregoing embodiments, the number does not have to be four. Instead, as can be seen from the relationship shown in Table 1 between the number of FIFO stages and the longer-side value, any other appropriate number may be selected for a line to be drawn.

EMBODIMENT 5

Hereinafter, a fifth embodiment of the present invention will be described with reference to the accompanying drawings.

In the foregoing fourth embodiment, the conventional line-drawing method using a linear parameter is adopted to draw a long line. In this fifth embodiment, the long line to be drawn is once divided into a plurality of short lines and then those short lines divided are drawn one after another.

Figure 22 illustrates a configuration for an X coordinate generator 2 for the line-drawing apparatus of the fifth embodiment. In Figure 22, the same components as those of the X coordinate generator 2 of the first embodiment shown in Figure 2 are identified by the same reference numerals and the description thereof will be omitted herein. As shown in Figure 22, the X coordinate generator 2 of the fifth embodiment

includes line-drawing FIFO memories **50** and dividing FIFO memories **51.** The line-drawing FIFO memories **50** include the first and second FIFO memories **11** and **12** shown in Figure **2.** The dividing FIFO memories **51** are connected in parallel to the line-drawing FIFO memories **50** and include memories with a function equivalent to that of the first and second FIFO memories **11** and **12.** Although not shown in Figure **22,** the dividing FIFO memories **51** are also provided for the Y coordinate generator.

Next, it will be described how to divide a long line.

Figure **23(a)** illustrates a long line **L1** to be drawn with a longer-side value of 9. As shown in Table 1, if the number of FIFO stages of each of the line-drawing FIFO memories **50** is four, then the longer-side value of the long line to be drawn is 5. In that case, the dividing FIFO memories **51** divide this long line **L1** into two, thereby generating first and second short lines **L2a** and **L2b** as shown in Figure **23(b).** Specifically, the first short line **L2a** starts at "1" and ends at "5", while the second short line **L2b** starts at "5" and ends at "9".

On the other hand, if the number of FIFO stages of each of the line-drawing FIFO memories **50** is two, then the longer-side value of the long line to be drawn is 3. In that case, the dividing FIFO memories **51** divide the long line **L1** into four, thereby generating first, second, third and fourth short lines **L3a, L3b, L3c** and **L3d** as shown in Figure **23(c).** Specifically, the first short line **L3a** starts at "1" and ends at

for determining the number of times the divide-by-two operation should be performed to divide the long line into short lines.

In this manner, according to the fifth embodiment, a long line is repeatedly divided in advance into short lines by the same method as that used to draw a short line until each of the short lines can be drawn. And then these short lines divided are drawn one after another. Accordingly, even a long line with a longer-side value exceeding that determined by the number of FIFO stages of the dividing FIFO memories **51** can be drawn without using the linear parameters. In addition, the long line **L1** is divided at its midpoint as is done in each embodiment of the present invention. Thus, just by providing the dividing FIFO memories **51** in parallel to the line-drawing FIFO memories **50** and adding the dividing ROM table **251B**, the other circuits and hardware resources can be shared. As a result, the line-drawing apparatus can have a simpler configuration.

Also, multiple line-drawing apparatuses of the first embodiment may be prepared. In that case, after a long line to be drawn has been divided into a plurality of short lines that can be drawn by these apparatuses, those short lines may be drawn by the same number of line-drawing apparatuses in parallel. In this manner, the long line can be drawn in a much shorter time.

"3", the second short line **L3b** starts at "3" and ends at "5",

the third short line **L3c** starts at "5" and ends at "7" and the

fourth short line **L3d** starts at "7" and ends at "9".

The following Table 3 is an example of a more practical

5 division number determination table:

[Table 3]

Longer-side value	Division Number	Number of times of Divide-by-two operation
3 through 33	1	0
34 through 65	2	1
66 through 129	4	3
130 through 257	8	7

As can be seen from Table 3, if the longer-side value is

up to 33 (i.e., if the number of stages of the line-drawing

FIFO memories **50** is 32 or less), then no divide-by-two opera-

10 tions need to be performed. It can also be seen that this

method is applicable to any long line with a longer-side value

of 257 or less.

Figure **24** illustrates a configuration for a number-of-

times comparator **25b** including the division number determina-

15 tion table. In Figure **24**, the same components as those illus-

trated in Figure **6** are identified by the same reference

numerals. As shown in Figure **24**, the number-of-times compara-

tor **25b** of the fifth embodiment includes line-drawing ROM ta-

ble **251A** and dividing ROM table **251B**. The line-drawing ROM

20 table **251A** is used for determining the number of times the

line-drawing operation should be performed to draw short

lines. On the other hand, the dividing ROM table **251B** is used

As for a line with a longer-side value greater than 257, the conventional method of drawing a line using its linear parameter may be additionally adopted as in the fourth embodiment.